



ENERGY STAR CERTIFIED

# Uninterruptible Power Supplies

## CyberPower - PR3000RTXL2UHVA : PR3000RTXL2UHVA

### Specifications

<b>ENERGY STAR Unique ID:</b>	2323355
<b>Brand Name:</b>	CyberPower
<b>Model Name:</b>	PR3000RTXL2UHVA
<b>Model Number:</b>	PR3000RTXL2UHVA
<b>Power Conversion Mechanism:</b>	Static
<b>Minimum Configuration Tested Model Number:</b>	PR3000RTXL2UHVA
<b>Active Output Power Rating Minimum Configuration (W):</b>	3000
<b>Apparent Output Power Rating Minimum Configuration (VA):</b>	3000
<b>Topology (ac):</b>	Line Interactive
<b>Topology and Product Type Combined:</b>	ac Line Interactive (VI)
<b>Application:</b>	Consumer
<b>Rated Input Voltage (V rms):</b>	200-240
<b>Rated Input Frequency (Hz):</b>	50-60
<b>Rated Output Voltage (V):</b>	200-240
<b>Rated Output Frequency (Hz):</b>	50-60
<b>Rack Mountable:</b>	Yes
<b>Rack Mount Height (U):</b>	2
<b>Height (mm):</b>	87
<b>Width (mm):</b>	433
<b>Depth (mm):</b>	630
<b>Normal Mode(s) Input Dependency Characteristic (ac):</b>	Voltage Independent
<b>Modular UPS:</b>	No
<b>Number of Normal Modes:</b>	Single-normal-mode
<b>Default Normal Mode (ac):</b>	Voltage Independent
<b>Test Input Voltage (V rms):</b>	230
<b>Test Input Frequency (Hz):</b>	6050
<b>Test Output Voltage (V):</b>	230
<b>Test Output Frequency (Hz):</b>	50
<b>Total Input Power in W at 0% Load Min Config Lowest Dependency (ac):</b>	5.8

<b>Efficiency at 25% Load Min Config Lowest Dependency (ac):</b>	99.1
<b>Efficiency at 50% Load Min Config Lowest Dependency (ac):</b>	99.0
<b>Efficiency at 75% Load Min Config Lowest Dependency (ac):</b>	98.9
<b>Efficiency at 100% Load Min Config Lowest Dependency (ac):</b>	98.8
<b>Weighted Efficiency Calc Min Config Lowest Dependency:</b>	98.9
<b>Efficiency (%):</b>	98.9
<b>Modular UPS Module Tested Model Number:</b>	N/A
<b>Energy Storage Mechanism:</b>	Battery
<b>Energy Storage System Technology:</b>	Valve Regulated Lead-acid Battery
<b>Energy Storage System Configuration:</b>	Integral
<b>Energy Storage System Removable to Another Room:</b>	No
<b>Energy Storage System Runtime at 100% Load (min.):</b>	4
<b>Energy Storage System Runtime at 50% Load (min.):</b>	11
<b>Energy Storage System Warranty (yrs):</b>	3
<b>Energy Storage System Information URL:</b>	N/A
<b>Network Connections Available:</b>	Serial Port,Ethernet,USB Port
<b>Communication Protocols:</b>	HTTP,HTTPS,Other,SNMP (v1, 2 or 3)
<b>Communication Protocol Other:</b>	TCP/IP, UDP
<b>Manufacturer Take Back Program:</b>	Yes
<b>Model Web Page URL:</b>	N/A
<b>Test Method Guidelines:</b>	N/A
<b>Date Available on Market:</b>	2018-08-01
<b>Date Certified:</b>	2023-01-17
<b>Markets:</b>	United States, Taiwan, Japan, Canada
<b>ENERGY STAR Certified:</b>	Yes

## Additional Model Information

ELITE PRO 2200ERTXL2UA,ELITE PRO 2200ERTXL2UA;; ELITE PRO 3000ERT2U,ELITE PRO 3000ERT2U;; ELITE PRO 3000ERTXL2U,ELITE PRO 3000ERTXL2U;; ELITE PRO 3000ERTXL2UA,ELITE PRO 3000ERTXL2UA;; PR2200ERTXL2UA JP,PR2200ERTXL2UA JP;; PR2200ERTXL2UA,PR2200ERTXL2UA;; PR2200RTXL2UHVA JP,PR2200RTXL2UHVA JP;; PR2200RTXL2UHVA,PR2200RTXL2UHVA;; PR3000ERT2U JP,PR3000ERT2U JP;; PR3000ERT2U,PR3000ERT2U;; PR3000ERTXL2U JP,PR3000ERTXL2U JP;; PR3000ERTXL2U,PR3000ERTXL2U;; PR3000ERTXL2UA JP,PR3000ERTXL2UA JP;; PR3000ERTXL2UA,PR3000ERTXL2UA;; PR3000RTXL2UHVA JP,PR3000RTXL2UHVA JP;; PX2200ERTXL2U,PX2200ERTXL2U;; PX3000ERTXL2U,PX3000ERTXL2U,

**Captured On:**  
04/25/2025