



ENERGY STAR CERTIFIED

## Uninterruptible Power Supplies

### APC by Schneider Electric - Back UPS PRO BR 1350VA SineWave 10 Outlets 2 USB Charging Ports AVR LCD interface : BR1350MS

#### Specifications

|  |   |
|--|---|
| ENERGY STAR Unique ID:                                   | 2333485   |
| Brand Name:  | APC by Schneider Electric   |
| Model Name:  | Back UPS PRO BR 1350VA SineWave 10 Outlets 2 USB Charging Ports AVR LCD interface |
| Model Number:  | BR1350MS  |
| Power Conversion Mechanism:                              | Static  |
| Minimum Configuration Tested Model Number:               | BR1350MS  |
| Active Output Power Rating Minimum Configuration (W):    | 810   |
| Apparent Output Power Rating Minimum Configuration (VA): | 1350  |
| Topology (ac):   | Line Interactive  |
| Topology and Product Type Combined:                      | ac Line Interactive (VI)  |
| Application:   | Consumer  |
| Rated Input Voltage (V rms):                             | 120-120   |
| Rated Input Frequency (Hz):                              | 60-60   |
| Rated Output Voltage (V):                                | 120-120   |
| Rated Output Frequency (Hz):                             | 60-60   |
| Rack Mountable:  | No  |
| Height (mm):   | 260   |
| Width (mm):  | 100   |
| Depth (mm):  | 368   |
| Total Number of Outlets:                                 | 10  |
| Number of Battery Backup and Surge Protected Outlets:    | 6   |
| Number of Surge Protected Only Outlets:                  | 4   |
| Normal Mode(s) Input Dependency Characteristic (ac):     | Voltage Independent   |
| Modular UPS:   | No  |
| Number of Normal Modes:                                  | Single-normal-mode  |
| Default Normal Mode (ac):                                | Voltage Independent   |
| Test Input Voltage (V rms):                              | 120   |

|   |   |
|---|---|
| <b>Test Input Frequency (Hz):</b>   | 60  |
| <b>Test Output Voltage (V):</b>   | 120   |
| <b>Test Output Frequency (Hz):</b>  | 60  |
| <b>Total Input Power in W at 0% Load Min Config Lowest Dependency (ac):</b> | 3.036   |
| <b>Efficiency at 25% Load Min Config Lowest Dependency (ac):</b>            | 98.3  |
| <b>Efficiency at 50% Load Min Config Lowest Dependency (ac):</b>            | 99.0  |
| <b>Efficiency at 75% Load Min Config Lowest Dependency (ac):</b>            | 99.1  |
| <b>Efficiency at 100% Load Min Config Lowest Dependency (ac):</b>           | 99.1  |
| <b>Weighted Efficiency Calc Min Config Lowest Dependency:</b>               | 99.1  |
| <b>Efficiency (%):</b>  | 99.1  |
| <b>Modular UPS Module Tested Model Number:</b>                              | N/A   |
| <b>Energy Storage Mechanism:</b>  | Battery   |
| <b>Energy Storage System Technology:</b>                                    | Valve Regulated Lead-acid Battery   |
| <b>Energy Storage System Configuration:</b>                                 | Integral  |
| <b>Energy Storage System Removable to Another Room:</b>                     | No  |
| <b>Energy Storage System Runtime at 100% Load (min.):</b>                   | 3   |
| <b>Energy Storage System Runtime at 50% Load (min.):</b>                    | 11  |
| <b>Energy Storage System Warranty (yrs):</b>                                | 3   |
| <b>Energy Storage System Information URL:</b>                               | <a href="http://www.apc.com/shop/us/en/products/P-APCRBC161">http://www.apc.com/shop/us/en/products/P-APCRBC161</a>   |
| <b>Battery Recycling URL:</b>   | <a href="http://www.apc.com/us/en/who-we-are/sustainability/recycling-options.jsp">http://www.apc.com/us/en/who-we-are/sustainability/recycling-options.jsp</a> |
| <b>Network Connections Available:</b>                                       | USB Port  |
| <b>Communication Protocols:</b>   | Other   |
| <b>Communication Protocol Other:</b>  | USB Power Summary   |
| <b>Manufacturer Take Back Program:</b>                                      | Yes   |
| <b>Manufacturer Take Back Program URL:</b>                                  | <a href="http://www.apc.com/us/en/who-we-are/sustainability/recycling-options.jsp">http://www.apc.com/us/en/who-we-are/sustainability/recycling-options.jsp</a> |
| <b>Model Web Page URL:</b>  | <a href="http://www.apc.com/shop/us/en/products/P-BR1350MS">http://www.apc.com/shop/us/en/products/P-BR1350MS</a>   |
| <b>Test Method Guidelines:</b>  | <a href="http://www.apc.com/us/en/who-we-are/sustainability/">http://www.apc.com/us/en/who-we-are/sustainability/</a>   |
| <b>Date Available on Market:</b>  | 2017-12-03  |
| <b>Date Certified:</b>  | 2019-02-12  |
| <b>Markets:</b>   | United States, Canada   |
| <b>ENERGY STAR Certified:</b>   | Yes   |

# Additional Model Information

Back UPS PRO BR 1350VA SineWave 10 Outlets 2 USB Charging Ports AVR LCD interface Factory Serviced,BR1350MSW,;  
Std Exch Back UPS PRO BR 1350VA SineWave 10 Outlets 2 USB Charging Ports AVR LCD interface,BR1350MSQ,

|           |              |
|-----------|--------------|
| UPC Codes | 731304335399 |
|-----------|--------------|

Captured On:  
05/23/2025