



ENERGY STAR CERTIFIED

# Uninterruptible Power Supplies

## CyberPower - PR1500LCD : PR1500LCD

### Specifications

<b>ENERGY STAR Unique ID:</b>	2331985
<b>Brand Name:</b>	CyberPower
<b>Model Name:</b>	PR1500LCD
<b>Model Number:</b>	PR1500LCD
<b>Power Conversion Mechanism:</b>	Static
<b>Minimum Configuration Tested Model Number:</b>	PR1500LCD
<b>Active Output Power Rating Minimum Configuration (W):</b>	1500
<b>Apparent Output Power Rating Minimum Configuration (VA):</b>	1500
<b>Topology (ac):</b>	Line Interactive
<b>Topology and Product Type Combined:</b>	ac Line Interactive (VI)
<b>Application:</b>	Consumer
<b>Rated Input Voltage (V rms):</b>	120-120
<b>Rated Input Frequency (Hz):</b>	50-60
<b>Rated Output Voltage (V):</b>	120-120
<b>Rated Output Frequency (Hz):</b>	50-60
<b>Rack Mountable:</b>	No
<b>Height (mm):</b>	222
<b>Width (mm):</b>	170
<b>Depth (mm):</b>	433
<b>Normal Mode(s) Input Dependency Characteristic (ac):</b>	Voltage Independent
<b>Modular UPS:</b>	No
<b>Number of Normal Modes:</b>	Single-normal-mode
<b>Default Normal Mode (ac):</b>	Voltage Independent
<b>Test Input Voltage (V rms):</b>	120
<b>Test Input Frequency (Hz):</b>	60
<b>Test Output Voltage (V):</b>	120
<b>Test Output Frequency (Hz):</b>	60
<b>Total Input Power in W at 0% Load Min Config Lowest Dependency (ac):</b>	5.3
<b>Efficiency at 25% Load Min Config Lowest Dependency (ac):</b>	98.3

<b>Efficiency at 50% Load Min Config Lowest Dependency (ac):</b>	98.7
<b>Efficiency at 75% Load Min Config Lowest Dependency (ac):</b>	98.5
<b>Efficiency at 100% Load Min Config Lowest Dependency (ac):</b>	98.2
<b>Weighted Efficiency Calc Min Config Lowest Dependency:</b>	98.5
<b>Efficiency (%):</b>	98.5
<b>Modular UPS Module Tested Model Number:</b>	N/A
<b>Energy Storage Mechanism:</b>	Battery
<b>Energy Storage System Technology:</b>	Valve Regulated Lead-acid Battery
<b>Energy Storage System Configuration:</b>	Integral
<b>Energy Storage System Removable to Another Room:</b>	No
<b>Energy Storage System Runtime at 100% Load (min.):</b>	4
<b>Energy Storage System Runtime at 50% Load (min.):</b>	15
<b>Energy Storage System Warranty (yrs):</b>	1
<b>Energy Storage System Information URL:</b>	N/A
<b>Network Connections Available:</b>	Serial Port,USB Port,Ethernet
<b>Communication Protocols:</b>	HTTPS,Other,HTTP,SNMP (v1, 2 or 3)
<b>Communication Protocol Other:</b>	HID, CyberPower serial Protocol (v2)
<b>Manufacturer Take Back Program:</b>	Yes
<b>Model Web Page URL:</b>	<a href="https://www.cyberpowersystems.com/product/ups/pr1500lcd/">https://www.cyberpowersystems.com/product/ups/pr1500lcd/</a>
<b>Test Method Guidelines:</b>	N/A
<b>Date Available on Market:</b>	2019-01-01
<b>Date Certified:</b>	2018-12-24
<b>Markets:</b>	United States, Canada
<b>ENERGY STAR Certified:</b>	Yes

## Additional Model Information

PR1000LCD,PR1000LCD,; PR1000LCDN,PR1000LCDN,; PR1000LCDNTAA,PR1000LCDNTAA,;  
PR1000LCDTAA,PR1000LCDTAA,; PR1500LCDN,PR1500LCDN,; PR1500LCDNTAA,PR1500LCDNTAA,; PR1500LCDTAA,P  
R1500LCDTAA,

**Captured On:**  
04/28/2025