

## Liebert - 10B14763GG103: 10B14763GG103

| Specifications  |  |
|---|--|
| ENERGY STAR Unique ID:  | 2470717  |
| Brand Name:   | Liebert  |
| Model Name:   | 10B14763GG103  |
| Model Number:   | 10B14763GG103  |
| Power Conversion Mechanism:   | Static   |
| Minimum Configuration Tested Model Number:                            | 10B14763GG103  |
| Active Output Power Rating Minimum Configuration (W):                 | 405000   |
| Apparent Output Power Rating Minimum Configuration (VA):              | 450000   |
| Topology (ac):  | Multi-Mode Double Conversion                                       |
| Topology and Product Type Combined:                                   | ac - Other   |
| Application:  | Data Center,Consumer,Commercial                                    |
| Rated Input Voltage (V rms):  | 430-528  |
| Rated Input Frequency (Hz):   | 45-66  |
| Rated Output Voltage (V):   | 480-480  |
| Rated Output Frequency (Hz):  | 50-60  |
| Rack Mountable:   | No   |
| Height (mm):  | 2150   |
| Width (mm):   | 1000   |
| Depth (mm):   | 900  |
| Normal Mode(s) Input Dependency Characteristic (ac):                  | Voltage and Frequency Independent, Voltage and Frequency Dependent |
| Modular UPS:  | No   |
| Number of Normal Modes:   | Multiple-normal-mode   |
| Default Normal Mode (ac):   | Voltage and Frequency Dependent                                    |
| Test Input Voltage (V rms):   | 480  |
| Test Input Frequency (Hz):  | 60   |
| Test Output Voltage (V):  | 480  |
| Test Output Frequency (Hz):   | 60   |
| Total Input Power in W at 0% Load Min Config Lowest Dependency (ac):  | 2917.84  |
| Total Input Power in W at 0% Load Min Config Highest Dependency (ac): | 973.13   |

| fficiency at 25% Load Min Config Lowest 96.1                            | 1   |
|---|---|
| fficiency at 25% Load Min Config Lowest 96.1 ependency (ac):            | I   |
| fficiency at 25% Load Min Config Highest 98.9 ependency (ac):           | 9   |
| fficiency at 50% Load Min Config Lowest 96.8 ependency (ac):            | 8   |
| fficiency at 50% Load Min Config Highest 99.3 ependency (ac):           | 3   |
| fficiency at 75% Load Min Config Lowest 96.7 ependency (ac):            | 7   |
| fficiency at 75% Load Min Config Highest 99.4 ependency (ac):           | 4   |
| fficiency at 100% Load Min Config Lowest 96.5 ependency (ac):           | 5   |
| fficiency at 100% Load Min Config Highest 99.4 ependency (ac):          | 4   |
| /eighted Efficiency Calc Min Config Lowest 96.6 ependency:              | 6   |
| /eighted Efficiency Calc Min Config Highest 99.2 ependency:             | 2   |
| linimum Configuration Input Power Factor 0.99 lighest-Input Dependency: | 9   |
| <b>fficiency (%):</b> 97.2  | 2   |
| Iodular UPS Module Tested Model Number: N/A                             | A   |
| nergy Storage Mechanism: Batt   | tery  |
| nergy Storage System Technology: Valv                                   | ve Regulated Lead-acid Battery  |
| nergy Storage System Configuration: Sep                                 | parate Enclosure  |
| nergy Storage System Removable to Another No oom:                       |   |
| nergy Storage System Runtime at 100% Load 15 nin.):                     |   |
| nergy Storage System Runtime at 50% Load 30 nin.):                      |   |
| nergy Storage System Warranty (yrs): 5                                  |   |
| nergy Storage System Information URL: http                              | o://www.enersys.com/ http://www.eastpennunigy.com/  |
| etwork Connections Available: Seri                                      | ial Port,Ethernet   |
| ommunication Protocols: Mod   | dbus TCP,SNMP (v1, 2 or 3),Modbus RTU   |
| lanufacturer Take Back Program: No                                      |   |
|   |   |
| est Method Guidelines: N/A  | os://www.vertiv.com/en-us/products-catalog/critical-power/<br>nterruptible-power-supplies-ups/liebert-exl-s1/ |
|   | nterruptible-power-supplies-ups/liebert-exl-s1/   |
| ate Available on Market: 202  | nterruptible-power-supplies-ups/liebert-exl-s1/   |
|   | nterruptible-power-supplies-ups/liebert-exl-s1/   |
| ate Certified: 202  | nterruptible-power-supplies-ups/liebert-exl-s1/   |